

## **460BCQT-N2E**

### **BACnet/IP Servers to MQTT**

#### **FEATURES**

- Fully configurable BACnet/IP client
- BACnet/IP supports device, binary I/O/V, analog I/O/V, multistate I/O/V, and character string value object types
- Bring your factory data to the cloud
- Support for MQTT, AWS and Azure
- Effortless Browser Based Configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- Guaranteed Stock
- 5-Year Hardware Warranty

#### **Connect BACnet/IP Server Devices to MQTT**

The 460BCQT moves data between up to 32 BACnet/IP devices and an MQTT application. Connect your BACnet/IP devices to cloud platforms such as AWS and Azure. Use the data to easily log data, build a dashboard or create a sophisticated alarm system. The 460BCQT delivers BACnet analog and binary data to MQTT topics in a JSON format.

Best of all, the product is made in the USA, always in stock, and comes with 5-year warranty.

#### How Do I Use the 460BCQT-N2E in My Application?

Analog and binary BACnet data values become topics published or subscribed to in an MQTT broker.

SSL transport layer security protects the data moving from your operations network to the cloud.

#### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

# **Specification**

BACnet/IP Client	
Operation Mode	BACnet/IP Client
Supported Object Types	Device, BI/BO/BV, AI/AO/AV, MI/MO/MV, Character String Value
Supported Service Codes	Read Property-A, Read Property Multiple-A, Write Property-A, Write Property Multiple-A, Device Dynamic Binding-A
Maximum Connections	32
Number Read/Write Scan Lines per Device	200 Total - 100 reads & 100 writes
Scan Line Support	Up to 128 Objects
MQTT	
Operation Mode	Generic MQTT, Amazon Web Services (AWS), Microsoft Azure
Max Broker Connections	Up to 3 Generic MQTT Connections, 1 AWS, 1 Azure
Max Data Points Per Connection	1000 Read and 1000 Write Topics
Security	SSL certificate based cloud access
Supported Data Formats	JSON
Data Payload	Topic Name and Value
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

ELECTRICAL / ENVIRONMENT	AL	
DC Input Voltage	12-24 VDC	
Maximum Baud Rate	115K baud	FI
Operating Temperature	-40 C to 85 C	<b>□ □</b>
Certification	RoHS-Compliant, UL, CUL, CE Approvals, Class I Div 2	3.83
ENCLOSURE / HARDWARE		
Size	5.40" x 3.83" x 1.19"	0 0
Weight	7.6 oz	
Enclosure Type	Anodized Aluminum	
Mounting	Din rail or panel mount	
LEDs	Power LED & 2 general purpose LEDs on side	
<b>GATEWAY FEATURES &amp; FUNC</b>	CTIONS	
Alarming	Set <, <=, >, >=, ==, !=, and change-of-state rules on any data moving through the gateway. If alarm rule is triggered an email notification can be sent.	
Gateway Security	You can configure up to 9 different users access to diagnostic and configuration screens.	
Translation Table	Allows for data manipulation during protocol translation. Scaling and other data format changes can occur in the gateway.	
Status and Counters	Protocol specific status, counters, and error messages are accessible within the gateway's diagnostics page. They can also be delivered to a connected device.	NOT EXACTLY WHAT YOU WERE L Real Time Automation offers a full line of Give us a call at 1-800-249-1612. Or, ch www.rtautomation.com/products. \ customizations for unique app
Diagnostic Logging Page	Allows users to see and log start up sequences, protocol specific messages & error messages.	
		The second secon

ocol specific status, counters, and error sages are accessible within the gateway's mostics page. They can also be delivered to a nected device.	NOT EXACTLY WHAT YOU WERE LOOKING FOR?  Real Time Automation offers a full line of gateway products.  Give us a call at 1-800-249-1612. Or, check out a listing at  www.rtautomation.com/products. We also offer  customizations for unique applications.
we users to see and log start up seguences	

CATALOG #	DESCRIPTION
460BCQT-N2E	Connect up to 32 BACnet/IP server devices to MQTT



Made in the



Always In

Stock





