

# 460MSQT-N2E

### Modbus TCP Client to MQTT

#### **FEATURES**

- Fully configurable Modbus TCP/IP server
- Move up to 100 groups of 512 contiguous coils or 512 contiguous registers to or from your Modbus TCP/IP client
- Bring your factory data to the cloud
- Support for MQTT, AWS and Azure
- Effortless Browser Based Configuration, no programming software is required
- Simple data translation allows you to manipulate data as it passes between protocols
- Guaranteed Stock
- 5-Year Hardware Warranty

### Bridge a Modbus TCP Controller to Cloud- Based Applications

The 460MSQT moves data between a Modbus TCP client device and an MQTT application, AWS or Azure. Use the data to easily log data, build a dashboard or create a sophisticated alarm system.

Best of all, the product is made in the USA, always in stock, and comes with 5-year warranty.

#### How Do I Use the 460MSQT-N2E in My Application?

Modbus register and coil data is mapped to and from topics in an MQTT broker.

SSL transport layer security protects the data moving from your operations network to the cloud.

#### Why Use Real Time Automation as a Gateway Supplier?

While there are certainly other companies offering protocol gateways, there is no one who provides the level of support and service that you receive from RTA.

When you call, a live person answers the phone. When you talk with sales, you will get honest answers and recommendations. When you get support, it is from an engineer who had a hand in the product's development, and support doesn't require a ticket or 24-hour wait.



A Solution, A Philosophy, the RTA Way. We understand the long hours spent on a factory floor and the pressure to keep a line running and product flowing. That's how Real Time Automation came to be. You want easy-to-use solutions where the hardest part is to open the box. You need customer support second to none. If you get all that and a fun customer experience all the better. Thirty years later, our mission remains the same: To move your data where you need it, when you need it, and how you need it.

## **Specification**

Modbus TCP Server	
Operation Mode	Modbus TCP/IP Server
Function Codes Supported	1,2,3,4,5,6, 15 & 16
Swapping	Byte and Word Swapping
Maximum Modbus TCP/IP Client Connections	10
Contiguous Data Areas	200 Total - 100 reads & 100 writes
Data Area Limits	512 Contiguous Coils or 512 Contiguous Registers
MQTT	
Operation Mode	Generic MQTT, Amazon Web Services (AWS), Microsoft Azure
Max Broker Connections	Up to 3 Generic MQTT Connections, 1 AWS, 1 Azure
Max Data Points Per Connection	1000 Read and 1000 Write Topics
Security	SSL certificate based cloud access
Supported Data Formats	JSON
Data Payload	Topic Name and Value
INCLUDED WITH GATEWAY	
3' power cable with flying leads	5-year hardware warranty
IPSetup software – automatically locates RTA gateway on the network	Unlimited firmware feature upgrades for life
CAT5 crossover cable for direct connection to PC during programming	Complete, unlimited access to our industry leading support staff
Manual	

#### **ELECTRICAL / ENVIRONMENTAL DC Input Voltage** 12-24 VDC 115K baud Maximum Baud Rate Operating Temperature -40 C to 85 C RoHS-Compliant, UL, CUL, CE Approvals, Class Certification 3.83 I Div 2 **ENCLOSURE / HARDWARE** 5.40" x 3.83" x 1.19" Size 0 Weight 7.6 oz Enclosure Type Anodized Aluminum . Mounting Din rail or panel mount Power LED & 2 general purpose LEDs on side LEDs 5.40 **GATEWAY FEATURES & FUNCTIONS** Set <, <=, >, >=, ==, !=, and change-of-state rules Alarming on any data moving through the gateway. If alarm rule is triggered an email notification can be sent. You can configure up to 9 different users access to Gateway Security diagnostic and configuration screens. Allows for data manipulation during protocol **Translation Table** translation. Scaling and other data format changes can occur in the gateway. NOT EXACTLY WHAT YOU WERE LOOKING FOR? Protocol specific status, counters, and error Real Time Automation offers a full line of gateway products. messages are accessible within the gateway's Status and Counters Give us a call at 1-800-249-1612. Or, check out a listing at diagnostics page. They can also be delivered to a www.rtautomation.com/products. We also offer connected device. customizations for unique applications. Allows users to see and log start up sequences, **Diagnostic Logging Page** protocol specific messages & error messages.

CATALOG #	DESCRIPTION
460MSQT-N2E	Easily and securely connect Modbus TCP client device to cloud applications




1.19

.01

**]**o

Made in the





Ready to Ship







#### **Real Time Automation, Inc.**

#### solutions@rtautomation.com

1-800-249-1612